Modbus UID 244

Display Name	0-based Addr	Type	9155 15kW	93E 30kW	93PM 50kW	93PM 60kW	93PM G2 200kW	BladeUPS	9155 30kW	9355	9395	9395P
IinA	256	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
IinB	257	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
IinC	258	Register	Yes	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
IbypassA	262	Register	No	Yes	Yes	Yes	Yes	No	No	No	Yes	Yes
IbypassB	263	Register	No	Yes	Yes	Yes	Yes	No	No	No	Yes	Yes
IbypassC	264	Register	No	Yes	Yes	Yes	Yes	No	No	No	Yes	Yes
IoutA	265	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
IoutB	266	Register	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
IoutC	267	Register	No	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
Battery Current	270	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Output Watts Rating	273	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Vab Input	277	Register	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Vbc Input	278	Register	No	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
Vca Input	279	Register	No	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
Van Bypass	286	Register	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Vbn Bypass	287	Register	No	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Vcn Bypass	288	Register	No	Yes	Yes	Yes	Yes	No	No	Yes	Yes	Yes
Vab Bypass	289	Register	No	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Vbc Bypass	290	Register	No	Yes	Yes	Yes	Yes	No	No	Yes	Yes	Yes
Vca Bypass	291	Register	No	Yes	Yes	Yes	Yes	No	No	Yes	Yes	Yes
Van Output	292	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Vbn Output	293	Register	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Vcn Output	294	Register	No	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
Vab Output	295	Register	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Vbc Output	296	Register	No	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
Vca Output	297	Register	No	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
Battery Voltage	301	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Watts Out	310	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
VA Out	311	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Percent Full Load	313	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Output PF	317	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Input Frequency	318	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Bypass Frequency	320	Register	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Output Frequency	321	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Battery Time Remaining	329	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Battery Capacity Remaining	331	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Van Input	336	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Vbn Input	337	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Vcn Input	338	Register	Yes	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes
Vendor Name	416	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Model Name	432	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Serial Number	440	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Part Number	448	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Reference Number	456	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Output VA Rating	521	Register	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Nominal Input Voltage	531	Register	No	Yes	Yes	Yes	Yes	No	No	No	No	No
System Output On	1024	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Inverter Output On	1025	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
System Alarm Active	1026	Discrete	No	Yes	Yes	Yes	Yes	No	No	No	Yes	Yes
Configuration Error	1027	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
UPS On Battery	1028	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Shutdown Imminent	1030	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
System On Bypass	1031	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Internal Communication Failure	1033	Discrete	No	Yes	Yes	Yes	Yes	No	No	No	Yes	Yes
Output Overload	1034	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Remote Emergency Power Off	1035	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Battery Test Failed	1037	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Check Fan	1038	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
High Efficiency/ESS	1047	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Battery Energized	1056	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Check Battery Switchgear	1067	Discrete	No	No	No	No	No	No	No	No	No	No
Battery Breaker	1071	Discrete	Yes	No	Yes	Yes	No	Yes	Yes	Yes	Yes	Yes
Site Wiring Fault	1090	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Utility Input Breaker	1091	Discrete	No	No	Yes	Yes	No	Yes	No	No	Yes	Yes
Utility Out Of Limits	1096	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Check Fuse	1097	Discrete	No	Yes	Yes	Yes	Yes	No	No	No	No	No
Charger Over Temperature	1098	Discrete	Yes	No	No	No	No	No	Yes	Yes	Yes	Yes
Input Under Or Over Frequency	1099	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
System Not Redundant	1111	Discrete	Yes	No	Yes	Yes	No	Yes	Yes	Yes	Yes	Yes
System On Maintenance Bypass	1121	Discrete	No	Yes	Yes	Yes	Yes	Yes	No	No	Yes	Yes
Bypass Utility Present	1127	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Bypass Under Or Over Frequency	1129	Discrete	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Bypass Breaker-Contactor	1134	Discrete	No	No	No	No	No	Yes	Yes	Yes	Yes	Yes
Check Static Switch	1136	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes

Display Name	0-based Addr	Type	9155 15kW	93E 30kW	93PM 50kW	93PM 60kW	93PM G2 200kW	BladeUPS	9155 30kW	9355	9395	9395P
Static Switch Over Temperature	1145	Discrete	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Check Charger	1168	Discrete	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Charger On	1169	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Check Inverter	1217	Discrete	Yes	Yes	Yes	Yes	Yes	No	No	No	Yes	Yes
Inverter Over Temperature Trip	1219	Discrete	No	No	No	No	No	No	Yes	Yes	Yes	Yes
Inverter Output Over Current	1220	Discrete	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Inverter Over Temperature	1226	Discrete	Yes	Yes	Yes	Yes	Yes	No	Yes	Yes	Yes	Yes
Output Short Circuit	1265	Discrete	No	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes	Yes